



This instruction sheet is relevant to Phoebe LED Terra Garden Spike part code: 6188

THANK YOU for buying this PHOEBE LED product. To help ensure this luminaire gives complete satisfaction please only use it according to the following instructions, and then pass the instructions to the appropriate person for retention and future reference.

Warning

1. Installation only to be carried out by a qualified electrician
2. 240V mains cable connection should be made with a suitable IP65 junction box
3. For surface mounting: Please ensure both the mounting surface and mounting fixtures are suitable and securely anchor the unit to your mounting surface
4. Do not operate if product is damaged

<p>Specifications</p> <ul style="list-style-type: none"> • 10W LED mains powered floodlight • IP65 rated for outdoor use • 820lm useful, 1000lm total • Suitable for electronic switching, electronic timers and PIR sensors • Constructed from ASA plastic, with diecast aluminium spike • 1 Metre VDE cable attached • 4000K cool white colour • Instant Full Light • Not Suitable for dimming 	<p>Dimensions (mm)</p>	
<p>1 Insert Spike / Prepare mounting Surface</p>	<p>3 Attach to spike / Attach to surface</p>	
<p>2 Tilt luminaire forward for easy access to mounting bracket</p>	<p>4 Tilt/rotate luminaire to desired angle and direction and tighten rotational adjustment screw</p>	
<p>5 Feed cable to Junction box</p>	<p>6 Wire to Junction Box</p> <p>Wiring Instructions</p> <ol style="list-style-type: none"> Installation only to be carried out by a qualified electrician 240V mains cable connection should be made with a suitable IP65 junction box Connect power lead to 240V mains electricity <p>IP65 Junction Box Brown = Live Green/Yellow = Earth Blue = Neutral</p>	

Images are for information only. Phoebe LED shall not be held liable for improper operation of the luminaire in circumstances where procedures and specifications have not been followed correctly.