

LED Filament GLS Crown Silver




Energy saving LED Crown Silver Filament lamp that features a silver reflective coating on the envelope to reflect all the light backwards into the fitting. This lamp is best suited for fittings which are designed to focus the light; by reflecting the light backwards, the lamp ensures that all the available light can be focussed. They also look great in decorative applications where glare needs to be reduced.

- 15,000 hour life, 7,500 switching cycles
- 2700K warm white
- Colour rendering index Ra≥80
- ES-E27 cap
- Clear finish
- Dimmable - DuoDim™ Technology compatible with both leading and trailing edge dimmers*
- Recommended for indoor use only

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Total Lumens (lm)	Incandescent Equivalent (W)	Dimensions (mm)		Energy Rating	Order Qty
								Dia	H		
Single Carton											
9998	5	240	ES-E27	Warm White	2700	470	40	60	104	A+	1

* The lamp is compatible with most dimmer switches, please refer to website for up-to-date list of compatible dimmer switches.



Lighting brilliance since 1878

5W LED Filament GLS Crown Silver Part Codes: 9998



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP400X	60W-400W	LED	1-5	Does not dim below 5%
Aurora	AU-DSP401	60W-400W	Leading	1-5	Steps from 0-50%
Aurora	AU-DSP651	75W-650W	Leading	1-5	Steps from 0-50%
Danlers	DP1D 400WIET	60W-400W	Leading	1-5	Steps from 0-60%
Danlers	DPDLED	5W-250W	Leading	1-5	Steps from 0-50%
Danlers	DSS1D 250W	40W-250W	Leading	1-5	Steps from 0-50%
Lutron	Commercial Panel Module HW/LP-RPM-4A-230		Trailing	1 - 108	Dims 16% - 95%
Lutron	Commercial HomeWorksQS/myRoom LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 240V, RP		Trailing	1 - 10	Dims 16% - 97%
Lutron	Commercial Grafik Integrate GXI-3104		Trailing	1 - 81	Dims 16% - 97%
Lutron	Residential Panel Module HW/LP-RPM-4A-230		Trailing	1 - 108	Dims 16% - 95%
Lutron	Residential Rania RNSU-452B		Trailing	2 - 33	Dims 17% - 96%
Lutron	Residential HomeWorksQS/myRoom LQSE-4A1-D/MQSE-4A1-D/MQSE-3A1/MQSE-2A1-D, 240V, RP		Trailing	1 - 10	Dims 16% - 97%
Lutron	Interface NGRX-ELVI-CE with Grafik Eye QS Main Unit, 240V		Trailing	1 - 88	Dims 19% - 95%
MK	K1521WHILV	40W-300W	Leading	1-5	Does not dim below 25%
MK	K1524WHILV	40W-300W	Leading	1-5	Does not dim below 20%
MK	K4511xxxLV	40W-220W	Leading	1-5	Does not dim below 25%
Eaton	P9131	60W-250W	Leading	1-5	Steps from 0-40%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-5	Does not dim below 15%
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-5	Does not dim below 15%
Zano	ZANOMO500	11W-50W	Leading	1-5	Steps from 0-50% Can flicker below 20%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Danlers: DSS1D 400W, DQDGDEU400W

Lighting brilliance since 1878