

## Astra Dimmer Compatibility



The below table is designed to help you choose a suitable dimmer switch for your Phoebe LED dimmable product.

Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP400X	60W-400W	LED	1-6	Dims to 100%,
Aurora	AU-DSP401	60W-400W	Leading	1-6	Dims to 100%,
Aurora	AU-DSP651	75W-650W	Leading	1-6	Dims to 100%,
Bell	250VA	250W Max	LED	1-6	Dims to 100%,
British General	881P	60W-400W	Leading	1-6	Dims to 100% smooth
Click	MD9042	60W-400W	LED	1-6	Dims 15% to 100% smooth
Denmans	CORE3010	60W-400W	Leading	1-6	Dims to 100% smooth
Denmans	CORE3011	60W-250W	Leading	1-6	Dims to 100% smooth
Eaton	P9131	60W-250W	Leading	1-6	Dims to 100% smooth
Eaton	P9142	60W-400W	Leading	1-6	Dims to 100% smooth
EuroLite	ECPC1LED250 PCB	120W Max	LED	1-6	Dims 10% to 100% smooth
Hamilton	741XLEDITB100	5W-100W	LED	1-6	Dims 15% to 100%
Hamilton	LifeStat ID4002	40W-400W	Leading	1-6	Dims 50% to 100%
Hamilton	LEDITB100	100W Max	LED	1-6	Dims 5% to 100% smooth
Hamilton	GRID100LED	100W Max	LED	1-6	Dims 10% to 100% smooth
Holder	17081-400-2W	60-400W	Leading	1-6	Dims 5% to 100%
Leviton	LEV1906MOD	100W Max	LED	1-6	Dims to 100% smooth
LDPE	KQP221W	15W-220W	LED	1-6	Dims 50% to 100%
MK	K1501WHILV	500W Max	LED	1-6	Dims 20% to 100% smooth
MK	K1521WHILV	40W-300W	Leading	1-6	Dims 30% to 100% smooth
MK	K1524WHILV	40W-300W	Leading	1-6	Dims 20% to 100% smooth
MK	K4511xxxLV	40W-220W	Leading	1-6	Dims 10% to 100%
PowerPro	PPDM1G1W250	60W-250W	Leading	1-6	Dims 20% to 100% smooth
PowerPro	PPDM1G1W400	60W-400W	Leading	1-6	Dims 20% to 100% smooth
Schneider Electric	GGBL6012LS	5W-100W	LED	1-6	Dims to 100%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-6	Dims 5% to 80% smooth
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-6	Dims 10% to 100% smooth
Varilight	V-DIM HQ2W	40-250W	Leading	1-6	Dims 40% to 100% smooth
ViMark	V1253	60W-400W	Universal	1-6	Dims 30% to 100% smooth
Zano	ZMC250	5W-250W	LED	1-6	Dims to 100% smooth
Zano	ZANOMO500	11W-50W	Leading	1-6	Dims to 100% smooth
Zano	ZGRIDLED150	150W Max	LED	1-6	Dims to 100% smooth

Lighting brilliance since 1878



Phoebe LED™ is a trading name of Crompton Lamps Limited  
 Crompton Lamps Limited registered in England and Wales No. 05590551  
 Registered office and correspondence address: Unit 2, Marrtree Business Park, Bowling Back Lane, Bradford BD4 8QE

**Tel:** +44 (0)1274 657 088 **Fax:** +44 (0)1274 657 087 **Email:** sales@phoebelcd.com **Web:** www.phoebelcd.com

All images and specifications are for illustration purposes only and are subject to change without notice.  
 E. & O. E. © Crompton Lamps Limited 2018