

# LED Antique Spiral Filament Candle Dimmable





Energy saving LED replacement lamp featuring LED filament technology. LED spiral filaments FPC (flexible printed circuit) series filament arrangement, allowing true omni-directional light output. Full clear antiquated glass lamp to closely mimic old fashioned traditional lamps.

- 15,000 hour life
- 7,500 switching cycles
- 2200K extra warm white
- Colour rendering index Ra≥80
- SES-E14 cap
- Antique bronze finish
- Dimmable DuoDim™ Technology compatible with both leading and trailing edge dimmers\*
- Recommended for indoor use only

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Total Lumens (lm)	Incandescent Equivalent (W)	Dimensions (mm) Dia H	Energy Rating	Order Qty
<b>Candle - Single Carton</b>										
10642	3	240	SES-E14	Extra Warm White	2200	200	20	35 97		1

\* The lamp is compatible with most dimmer switches, please refer to the following pages for up-to-date list of compatible dimmer switches.



*Lighting brilliance since 1878*

## LED Antique Spiral Filament Candle Dimmable



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP401	60W-400W	Leading	1-5	Steps 0 - 20%
Aurora	AU-DSP651	75W-650W	Leading	1-5	Steps 0 - 20% Flickers 95 - 100%
Aurora	AU-DSP400X	60W-400W	LED	1-5	Slight flicker at all levels
Danlers	DQDGEU400W	40W-400W	Trailing	1-5	Does not dim below 50%
Danlers	DSS1D 250W	40W-250W	Leading	1-5	Steps 0 - 50%
Danlers	DP1D 400WIET	60W-400W	Leading	1-5	Steps 0 - 20%
Danlers	DPDLED	5W-250W	Leading	1-5	Steps 0 - 20%
Zano	ZGRIDLED	5W-250W	LED	1-5	Dims smooth 5 - 100%
Zano	ZANOMO500	11W-50W	Leading	1-5	Dims 0 - 100% Steps 0 - 20%
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-5	Dims smooth 0 - 100%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-5	Dims smooth 0 - 100%
Eaton	P9131	60W-250W	Leading	1-5	Dims 0 - 80% Steps 0 - 20%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Danlers: DSS1D 400W

*Lighting brilliance since 1878*