

LED PAR30 Dimmable



LED PAR (Pressed Aluminium Reflector) lamps feature a glass enclosure and highly reflective aluminium coating applied internally.



- 15,000 hour life
- 30,000 switching cycles
- ES-E27 cap
- Colour rendering index Ra≥80
- Prismatic lens
- DuoDim™ Technology compatible with both leading and trailing edge dimmers*
- Recommended for indoor use only

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Useful Lumens (lm)	Total Lumens (lm)	Halogen Equiv. (W)	Beam Angle	Dimensions (mm)		Energy Rating	Order Qty
										Dia	H		

PAR30 Dimmable*- Single Carton

4597	9	240	ES-E27	Warm White	2700	600	820	75	30°	95	95	A+	1
------	---	-----	--------	------------	------	-----	-----	----	-----	----	----	----	---

* The lamp is compatible with most dimmer switches, please refer to following pages for up-to-date list of compatible dimmer switches.



Lighting brilliance since 1878

LED PAR30 Dimmable Part Codes: 4597



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP401	60W-400W	Leading	1-4	Steps from 0%-30%
Aurora	AU-DSP651	75W-650W	Leading	1-4	Steps from 0%-40%
Aurora	AU-DSP400X	60W-400W	LED	1-4	Steps from 0%-30%
Danlers	DSS1D 250W	40W-250W	Leading	1-4	Steps from 0%-40%
Danlers	DP1D 400WIET	60W-400W	Leading	1-4	Steps from 0%-30%
Danlers	DPDLED	5W-250W	Leading	1-4	Steps from 0%-30%
MK	K4511xxxLV	40W-220W	Leading	1-4	Steps from 0%-30%
MK	K1521WHILV	40W-300W	Leading	1-4	Steps from 0%-40%
MK	K1523WHILV	40W-300W	Leading	1-4	Steps from 0%-30%
Zano	ZANOMO500	11W-50W	Leading	1-4	Steps from 0%-30%
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-4	Dims 40%-100%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-4	Dims 40%-100%
Eaton	P9131	60W-250W	Leading	1-4	Steps from 0%-30%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Danlers: DSS1D 400W, DQDGDEU400W

Lighting brilliance since 1878