

LED GU10 Glass SMD 5.5W Sunset Dim





Energy efficient LED retrofit GU10 lamp. Dims from 3000K to 2200K. 25,000 hour life. 50,000 switching cycles. GU10 cap. Suitable for fire rated downlights.

- 25,000 hour life
- 50,000 switching cycles
- Features Sunset Dim technology; as the lamp is dimmed the colour temperature becomes warmer to recreate the cosy feeling of a traditional lamp
- 3000K warm white at full power; 2200K extra warm white when dimmed to 10%
- DuoDim™ Technology compatible with both leading and trailing edge dimmers*
- Suitable for fire rated downlights
- Recommended for indoor use only
- Instant full light

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Useful Lumens (lm)	Total Lumens (lm)	Halogen Equiv. (W)	Beam Angle	Dimensions (mm)		Energy Rating	Order Qty
										Dia	H		
Single Carton													
9738	5.5	240	GU10	Warm White/ Extra Warm White	3000/ 2200	300	360	50	50°	50	56	A	1

* The lamp is compatible with most dimmer switches, please refer to following pages for up-to-date list of compatible dimmer switches.



Lighting brilliance since 1878

LED GU10 Glass SMD 5.5W Sunset Dim Part Codes: 9738



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP401	60W-400W	Leading	1-3	Dims smooth 0%-100%
Aurora	AU-DSP651	75W-650W	Leading	1-3	Steps from 0%-30%
Aurora	AU-DSP400X	60W-400W	LED	1-3	Dims 25%-100%
Danlers	DSS1D 250W	40W-250W	Leading	1-3	Steps 0%-25%
Danlers	DP1D 400WIET	60W-400W	Leading	1-3	Steps 0%-20%
Danlers	DSS1D 400W	60W-400W	Leading	1-3	Dims 10%-100%
Danlers	DQDGDEU400W	40W-400W	Trailing	1-3	Dims smooth 0%-100%
Danlers	DPDLED	5W-250W	Leading	1-3	Dims 40%-100%
Click	MD9042	60W-400W	LED	1-3	Dims smooth 0%-100%
Core	3010	60W-400W	Leading	1-3	Steps from 0%-40%
Core	3011	60W-250W	Leading	1-3	Dims 20%-100%
Eaton	P9131	60W-250W	Leading	1-3	Steps from 0%-30%
Eaton	P9141	60W-400W	Leading	1-3	Steps from 0%-40%
Hamilton	741XLEDITB100	5W-100W	LED	1-3	Dims 0%-100%
Leviton	LEV71906MOD	100W Max	Leading	1-3	Dims 20%-100%
MK	K1523WHILV	40W-300W	Leading	1-3	Dims smooth 0%-100%
MK	K34101G1W	40W-300W	Leading	1-3	Dims 0%-75%
MK	K4511xxLV	40W-220W	Leading	1-3	Dims 5%-100%
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-3	Dims 5%-100%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-3	Dims 0%-75%
Zano	ZANOMO500	11W-50W	Leading	1-3	Steps from 0%-20%
Zano	ZGridLED	5W-250W	LED	1-3	Dims 0%-60%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Lighting brilliance since 1878