

Firesafe All-in-One Fire-Rated LED Downlight

Part Code: 12639



The below table is designed to help you choose a suitable dimmer switch for your Phoebe LED dimmable product.

Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
CLICK	MD9014	100W	LED	1-6	Dims smooth 0 - 100%
CLICK	MD9042	60-400W	LED	1-4	Dims 50 - 100%
Hamilton	GRID100LED	5W-100W	Leading	1-6	Dims 40 - 100%
Hamilton	741XLEDITB100	5W-100W	LED	1-6	Dims 40 - 100%
MK	K1523WHILV	4W-70W	LED	1-6	Dims 40 - 100%
Variilight	V-Pro JQP401W	10W-400W	Trailing	1-6	Dims smooth 25 - 100%
Variilight	V-Pro JQP252W	10W-250W	Trailing	1-6	Dims smooth 25 - 100%
Zano	ZMC250	5W-250W	LED	1-6	Dims smooth 20 - 100%

Lighting brilliance since 1878



Phoebe LED™ is a trading name of Crompton Lamps Limited
 Crompton Lamps Limited registered in England and Wales No. 05590551
 Registered office and correspondence address: Unit 2, Marrtree Business Park, Bowling Back Lane, Bradford BD4 8QE
Tel: +44 (0)1274 657 088 **Fax:** +44 (0)1274 657 087 **Email:** sales@cromptonlamps.com **Web:** www.cromptonlamps.com

All images and specifications are for illustration purposes only and are subject to change without notice.
 E. & O. E. © Crompton Lamps Limited 2020