



LED AR111 12.5W Direct Retrofit




LED AR11 Retrofit. Energy saving with low power consumption. Typical uses include bars, restaurants, retail display and hotels. For use in display lighting.

- Energy saving direct retrofit LED AR111
- 15.000 hour life
- 30,000 switching cycles
- Available as 12V G53 retrofit, or with 240V GU10 cap
- 3000K warm white or 4000K cool white colour temperature
- Colour rendering index Ra≥80
- Exact shape and size as traditional halogen AR111
- Instant full light
- Suitable for indoor use only
- Not suitable for dimming

| Product Code | Watts* (W) | Volts (V) | Cap | Colour Appearance | Colour Temp | Useful Lumens | | Approx. Beam Halogen Angle | | | | Energy Rating | Order Qty |
|--------------------|---------------|--------------|------|----------------------|----------------|------------------|------|-------------------------------|-----|-----|----|------------------|--------------|
| | | | | | (K) | (lm) | (lm) | Equiv. (W) | | Dia | Н | | |
| 12V Single Carton | | | | | | | | | | | | | |
| 9127 | 12.5 | 12 | G53 | Warm White | 3000 | 850 | 920 | 100 | 30° | 111 | 62 | Α | 1 |
| 9943 | 12.5 | 12 | G53 | Cool White | 4000 | 870 | 940 | 100 | 30° | 111 | 62 | Α | 1 |
| 240V Single Carton | | | | | | | | | | | | | |
| 9950 | 12.5 | 240 | GU10 | Warm White | 3000 | 910 | 990 | 100 | 30° | 111 | 62 | Α | 1 |
| 9967 | 12.5 | 240 | GU10 | Cool White | 4000 | 930 | 1010 | 100 | 30° | 111 | 62 | A | 1 |

^{*} Crompton 12V LED AR111 will operate with most AC or DC 12V transformers. However, some 12V transformers may have a minimum required load which may not be met when installing low powered LEDs; these transformers may cause flickering or the LEDs not to function correctly. If this issue arises it may be necessary to source a suitable LED Driver. If in doubt please contact Crompton Lamps for advice.















ighting brilliance since 1878

140 YEARS